

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.

AMENDMENTS TO THE CLAIMS

1. (Currently Amended) A method of demodulating a stereo composite signal including a pilot signal, comprising the steps of:

(a) sampling the stereo composite signal at a fixed sampling frequency, ~~thereby obtaining~~ to obtain input samples;

(b) processing the input samples to obtain internal samples having variable sampling timings;

(c) generating a reference signal according to the variable sampling timings;

(d) detecting a phase difference between the pilot signal and the reference signal using the internal samples;

(e) varying the variable sampling timings according to the detected phase difference; and

(f) digitally processing the internal samples to obtain stereo audio data.

2. (Original) The method of claim 1, wherein said step (b) comprises decimating the input samples with a variable decimation interval, and said step (e) comprises varying the decimation interval.

3. (Original) The method of claim 1, wherein said step (b) comprises using filter coefficients to perform an interpolation process on the input samples, the internal samples thus being obtained by interpolation, and said step (e) comprises changing the

filter coefficients.

4. (Original) The method of claim 3, wherein:

said step (e) further comprises selecting the filter coefficients from a plurality of sets of filter coefficients yielding internal samples interpolated at different temporal distances from a most recent input sample, the plurality of sets including at least a first set of filter coefficients interpolating an internal sample at a shortest of said temporal distances from the most recent input sample, and a second set of filter coefficients interpolating an internal sample at a longest of said temporal distances from the most recent sample.

5. (Original) The method of claim 4, wherein said step (b) further comprises the steps of:

skipping generation of an internal sample for the most recent input sample when the filter coefficients are changed from the first set to the second set; and

generating two internal samples for the most recent input sample, using both the first set of filter coefficients and the second set of filter coefficients, when the filter coefficients are changed from the second set to the first set.

6. (Original) The method of claim 4, wherein said step (b) further comprises the step of delaying starting timings of the

interpolation process according to said temporal distances from the most recent input sample.

7. (Original) The method of claim 1, wherein said step (f) comprises performing an interpolation process on the internal samples, thereby generating the stereo audio data at regular intervals.

8. (Currently Amended) The method of claim 1, wherein said step (f) comprises generating a pilot replica signal from the internal samples, and subtracting the pilot replica signal from the internal samples, ~~thereby canceling~~ to cancel the pilot signal.

9. (Currently Amended) A digital FM stereo demodulator for demodulating a stereo composite signal including a pilot signal, comprising:

means for obtaining input samples of the stereo composite signal, the input samples being sampled at a fixed sampling frequency;

means for processing the input samples to obtain internal samples having variable sampling timings;

means for generating a reference signal according to the variable sampling timings;

means for detecting a phase difference between the pilot signal and the reference signal using the internal samples;

means for varying the variable sampling timings according to the detected phase difference; and

means for digitally processing the internal samples to obtain stereo audio data.

10. (Original) The digital FM stereo demodulator of claim 9, wherein said means for processing comprises a decimator decimating the input samples with a variable decimation interval, and said means for varying varies the decimation interval.

11. (Original) The digital FM stereo demodulator of claim 9, wherein said means for processing comprises an interpolation filter using filter coefficients to perform an interpolation process on the input samples, the internal samples thus being obtained by interpolation, and said means for varying changes the filter coefficients.

12. (Original) The digital FM stereo demodulator of claim 11, further comprising a filter coefficient table storing a plurality of sets of filter coefficients yielding interpolated samples interpolated at different temporal distances from a most recent input sample, the plurality of sets including at least a first set of filter coefficients interpolating an internal sample at a shortest of said temporal distances from the most recent input sample, and a second set of filter coefficients interpolating an

internal sample at a longest of said temporal distances from the most recent sample.

13. (Original) The digital FM stereo demodulator of claim 12, further comprising a filter operation controller activating said interpolation filter as the input samples are obtained, skipping activation of the interpolation filter when said means for varying changes from the first set of filter coefficients to the second set of filter coefficients, and activating the interpolation filter twice, using both the first set of filter coefficients and the second set of filter coefficients, when the means for varying changes from the second set of filter coefficients to the first set of filter coefficients.

14. (Original) The digital FM stereo demodulator of claim 13, wherein the filter operation controller delays activation of the interpolation filter according to said temporal distances from the most recent input sample.

15. (Original) The digital FM stereo demodulator of claim 9, wherein said means for digitally processing comprises at least one interpolation filter performing an interpolation process on the internal samples, thereby generating the stereo audio data at regular intervals.

16. (Original) The digital FM stereo demodulator of claim 9, wherein said means for digitally processing generates a pilot replica signal from the internal samples, and subtracts the pilot replica signal from the internal samples, thereby canceling the pilot signal.

17. (New) An apparatus for demodulating a stereo composite signal, comprising:

- a converter to generate digital input samples of a received stereo composite signal carrying a pilot signal;

- a first processor to generate internal samples from the input samples using a variable internal sampling frequency;

- a signal generator to generate a reference signal based on the variable internal sampling frequency;

- a detector to detect phase difference between the pilot signal and the reference signal using the internal samples;

- a controller to vary the variable internal sampling frequency based on the detected phase difference; and

- at least a second processor to generate stereo audio data from the internal samples.

18. (New) The apparatus of claim 17, wherein said first processor includes a decimator having a decimation interval being varied by the controller to vary the internal sampling frequency.

19. (New) The apparatus of claim 17, wherein said first processor includes a filter to generate said input samples using interpolation and having coefficients being varied by the controller to vary the internal sampling frequency.

20. (New) A machine-readable medium having stored thereon a plurality of executable instructions, the plurality of instructions comprising instructions to:

generate digital input samples of a received stereo composite signal carrying a pilot signal;

generate internal samples from the input samples using a variable internal sampling frequency;

generate a reference signal based on the variable internal sampling frequency;

detect phase difference between the pilot signal and the reference signal using the internal samples;

vary the variable internal sampling frequency based on the detected phase difference; and

generate stereo audio data from the internal samples.

21. (New) The medium of claim 20, wherein said instructions to generate include instructions to generate said internal samples by decimation using a decimation interval being varied to vary the internal sampling frequency.

22. (New) The medium of claim 20, wherein said instructions to generate include instructions to generate said internal samples by interpolation using coefficients being varied by the controller to vary the internal sampling frequency.